



## VERTEC VT4889 VT4880A V4 PRESETS

### Crown I-Tech HD (26 dB Gain)



NAME	PRESET	DESCRIPTION	CH 1	CH 2
HF / HF 4889	2	VT4889 High Section Processing	4889 HI	4889 HI
MF / MF 4889	3	VT4889 Mid Section Processing	4889 MID	4889 MID
HF / MF 4889	4	VT4889 High/Mid Processing	4889 HI	4889 MID
MF / HF 4889	5	VT4889 Mid/High Processing	4889 MID	4889 HI
LF / LF 4889 3WX	6	VT4889 Low Section Processing: Fullrange Operation (30 Hz HPF, extended LF response)	4889 LOW	4889 LOW
	7	<i>empty (intentionally blank)</i>		
HF 4889 / SUB 4880A X	8	VT4889 High Section Processing / VT4880A X Processing (24-80 Hz; Inverted Polarity)	4889 HI	4880A SUB
MF 4889 / SUB 4880A X	9	VT4889 Mid Section Processing / VT4880A X Processing (24-80 Hz; Inverted Polarity)	4889 MID	4880A SUB
LF 4889 / SUB 4880A X	10	VT4889 Low Section X Processing (30 Hz HPF) / VT4880A X Processing (24-80 Hz; Inverted Polarity)	4889 LOW	4880A SUB
LF / LF 4889 4880A X	11	VT4889 Low Section X Processing (30 Hz HPF); for use with SUB/SUB 4880A 4889 X	4889 LOW	4889 LOW
SUB / SUB 4880A 4889 X	12	VT4880A X Processing (24-80 Hz; Inverted Polarity); for use with LF/LF 4889 4880A X	4880A SUB	4880A SUB
	13	<i>empty (intentionally blank)</i>		
HF 4889 / SUB 4880A 60	14	VT4889 High Section Processing / VT4880A (60 Hz LPF)	4889 HI	4880A SUB
MF 4889 / SUB 4880A 60	15	VT4889 Mid Section Processing / VT4880A (60 Hz LPF)	4889 MID	4880A SUB
LF 4889 / SUB 4880A 60	16	VT4889 Low Section (60 Hz HPF) / VT4880A (60 Hz LPF)	4889 LOW	4880A SUB
LF / LF 4889 4880A 60	17	VT4889 Low Section (60 Hz HPF); for use with SUB/SUB 4880A 4889 60	4889 LOW	4889 LOW
SUB / SUB 4880A 4889 60	18	VT4880A 60 Hz Processing (24-60 Hz); for use with LF/LF 4889 4880A 60	4880A SUB	4880A SUB
	19	<i>empty (intentionally blank)</i>		
HF 4889 / SUB 4880A 80	20	VT4889 High Section Processing / VT4880A (80 Hz LPF)	4889 HI	4880A SUB
MF 4889 / SUB 4880A 80	21	VT4889 Mid Section Processing / VT4880A (80 Hz LPF)	4889 MID	4880A SUB
LF 4889 / SUB 4880A 90	22	VT4889 Low Section (80 Hz HPF) / VT4880A (80 Hz LPF)	4889 LOW	4880A SUB
LF / LF 4889 4880A 80	23	VT4889 Low Section (80 Hz HPF); for use with SUB/SUB 4880A 4889 80	4889 LOW	4889 LOW
SUB / SUB 4880A 4889 80	24	VT4880A 80 Hz Processing (24-80 Hz); for use with LF/LF 4889 4880A 80	4880A SUB	4880A SUB