

JBL PD6212/66 Passive FIR Rotated Configuration for Crown ITech HD & ITHD 4x3500  
Tabulated DSP Parameters

Parameter	PD6212/66-H FR FIR
High Pass Type (IIR)	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	106Hz
Filter #1 Gain	+2.4dB
Filter #1 Q	Q0.8
Filter #2 Type	Parametric EQ
Filter #2 Frequency	82.5Hz
Filter #2 Gain	-0.9dB
Filter #2 Q	Q4.42
Filter #3 Type	Parametric EQ
Filter #3 Frequency	165Hz
Filter #3 Gain	+6.4dB
Filter #3 Q	Q2.05
Filter #4 Type	Parametric EQ
Filter #4 Frequency	945Hz
Filter #4 Gain	-2.0dB
Filter #4 Q	Q10.0
Filter #5 Type	Parametric EQ
Filter #5 Frequency	487Hz
Filter #5 Gain	-1.7dB
Filter #5 Q	Q2.37
Filter #6 Type	Parametric EQ
Filter #6 Frequency	762Hz
Filter #6 Gain	+1.5dB
Filter #6 Q	Q9.28
Filter #7 Type	Parametric EQ
Filter #7 Frequency	828Hz
Filter #7 Gain	+4.2dB
Filter #7 Q	Q12.0
Filter #8 Type	Parametric EQ
Filter #8 Frequency	912Hz

Filter #8 Gain	+6.1dB
Filter #8 Q	Q4.42