

JBL PD6200/43 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

| Parameter | PD6200/43 MHF FIR |
|--|---|
| High Pass Type (IIR) High Pass Frequency | Butterworth 24dB/oct 203Hz |
| Low Pass Type Low Pass Frequency | -- -- |
| Bandpass Gain Output Polarity Output Delay | +1dB (+) Non-Inverting 0.0 ms |
| Filter #1 Type Filter #1 Frequency Filter #1 Gain Filter #1 Q | Parametric EQ 240Hz +1.1dB Q3.1 |
| Filter #2 Type Filter #2 Frequency Filter #2 Gain Filter #2 Q | Parametric EQ 631Hz -2.4dB Q1.45 |
| Filter #3 Type Filter #3 Frequency Filter #3 Gain Filter #3 Q | Parametric EQ 419Hz -2.3dB Q1.98 |