

JBL PD6200/64 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/64 MHF FIR
High Pass Type (IIR) High Pass Frequency	Butterworth 24dB/oct 205Hz
Low Pass Type Low Pass Frequency	-- --
Bandpass Gain Output Polarity Output Delay	+1dB (+) Non-Inverting 0.0 ms
Filter #1 Type Filter #1 Frequency Filter #1 Gain Filter #1 Q	Parametric EQ 357Hz -2.2dB Q3.2
Filter #2 Type Filter #2 Frequency Filter #2 Gain Filter #2 Q	Parametric EQ 589Hz -4.2dB Q1.32
Filter #3 Type Filter #3 Frequency Filter #3 Gain Filter #3 Q	Parametric EQ 533Hz -1.8dB Q13.4