

JBL PD6200/95 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/95 MHF FIR
High Pass Type (IIR) High Pass Frequency	Butterworth 24dB/oct 205Hz
Low Pass Type Low Pass Frequency	-- --
Bandpass Gain Output Polarity Output Delay	-0.6dB (+) Non-Inverting 0.0 ms
Filter #1 Type Filter #1 Frequency Filter #1 Gain Filter #1 Q	Parametric EQ 645Hz -2.2dB Q7.8
Filter #2 Type Filter #2 Frequency Filter #2 Gain Filter #2 Q	Parametric EQ 457Hz -4.5dB Q2.0