

JBL PD6212/66 Passive IIR Configuration for BSS London Blu
 Tabulated DSP Parameters

Parameter	PD6212/66 FR IIR
High Pass Type	24 But
High Pass Frequency	76.8Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	84Hz
Filter #1 Boost/Cut	-1.3dB
Filter #1 Width	0.42 Oct
Filter #2 Type	Bell
Filter #2 Frequency	165Hz
Filter #2 Boost/Cut	+7.0dB
Filter #2 Width	0.69 Oct
Filter #3 Type	Bell
Filter #3 Frequency	481Hz
Filter #3 Boost/Cut	-1.7dB
Filter #3 Width	0.69 Oct
Filter #4 Type	Bell
Filter #4 Frequency	837Hz
Filter #4 Boost/Cut	+8.5dB
Filter #4 Width	0.16 Oct
Filter #5 Type	Bell
Filter #5 Frequency	1.09kHz
Filter #5 Boost/Cut	+3.6dB
Filter #5 Width	0.34 Oct
Filter #6 Type	Bell
Filter #6 Frequency	2.55kHz
Filter #6 Boost/Cut	-2.0dB
Filter #6 Width	1.56 Oct
Filter #7 Type	Bell
Filter #7 Frequency	7.1kHz
Filter #7 Boost/Cut	+2.0dB
Filter #7 Width	0.25 Oct
Filter #8 Type	Bell
Filter #8 Frequency	9.7kHz
Filter #8 Boost/Cut	+4.3dB

Filter #8 Width	0.59 Oct
-----------------	----------