



VT4883 VT4886 LONG THROW MIXED VT V4 Crown I-Tech (26 dB Gain)



NAME	PRESET	DESCRIPTION	CH 1	CH 2
MIXED 4883 / 4886 LONG THROW PRESETS				
VT4883 80 VT4886 LT	1	* Longthrow preset: 80 Hz crossover point; HF pre-emphasis (optional: use with 4881A, 4882, 4880 or 4880A X)	VT4883	VT4886
VT4883 120 VT4886 LT	2	** Longthrow preset: 120 Hz crossover point; HF pre-emphasis (optional: use with 4881A, 4882, 4880 or 4880A X)	VT4883	VT4886
VT4883 160 VT4886 LT	3	** Longthrow preset: 160 Hz crossover point; HF pre-emphasis (optional: use with 4881A, 4882, 4880 or 4880A X)	VT4883	VT4886
VT4883 300 VT4886 LT	4	** Longthrow preset: 300 Hz crossover point; HF pre-emphasis (optional: use with 4881A, 4882, 4880 or 4880A X)	VT4883	VT4886
	5	INTENTIONALLY BLANK		
VT4883 60-120 VT4886 LT	6	** Longthrow preset: 120 Hz crossover point; HF pre-emphasis (for use with 4881A, 4882, 4880 or 4880A 60)	VT4883	VT4886
VT4883 60-160 VT4886 LT	7	** Longthrow preset: 160 Hz crossover point; HF pre-emphasis (for use with 4881A, 4882, 4880 or 4880A 60)	VT4883	VT4886
VT4883 60-300 VT4886 LT	8	** Longthrow preset: 300 Hz crossover point; HF pre-emphasis (for use with 4881A, 4882, 4880 or 4880A 60)	VT4883	VT4886
	9	INTENTIONALLY BLANK		
VT SUB PROCESSING : VT4881A, VT4882, VT4880, VT4880A (X MODE : USE WITH VT4883 80, 120, 160, 300) ; (60 MODE : USE WITH 60-120, 60-160, 60-300)				
VT4881A 60	10	VT4881A: 27 - 60 Hz, positive polarity, pre-aligned to VT4883 60-120, 60-160, 60-300	VT4881A	VT4881A
VT4881A X	11	VT4881A: 27 - 80 Hz, inverted polarity, pre-aligned to VT4883 80,120,160,300	VT4881A	VT4881A
	12	INTENTIONALLY BLANK		
VT4882 60	13	VT4882: 29 - 60 Hz, positive polarity, pre-aligned to VT4883 60-120, 60-160, 60-300	VT4882	VT4882
VT4882 X	14	VT4882: 29 - 80 Hz, inverted polarity, pre-aligned to VT4883 80,120,160,300	VT4882	VT4882
	15	INTENTIONALLY BLANK		
VT4880 60	16	VT4880: 26 - 80 Hz, positive polarity, pre-aligned to VT4883 60-120, 60-160, 60-300	VT4880	VT4880
VT4880 X	17	VT4880: 26 - 80 Hz, inverted polarity, pre-aligned to VT4883 80,120,160,300	VT4880	VT4880
	18	INTENTIONALLY BLANK		
VT4880A 60	19	VT4880A: 25 - 60 Hz, positive polarity, pre-aligned to VT4883 60-120, 60-160, 60-300	VT4880A	VT4880A
VT4880A X	20	VT4880A: 25 - 80 Hz, inverted polarity, pre-aligned to VT4883 80,120,160,300	VT4880A	VT4880A

- NOTES
- * Physically Separate configuration (VT4886 + UB-1 + SS5-BK extension rod + VT4883 or flown VT4886 + ground stacked VT4883)
Additional time delay required to account for geometric path difference between VT4886 and VT4883
Enable optional Input PEQ1 for use in Closely Coupled configurations (VT4886 stacked on top of VT4883 or suspended below VT4883)
 - ** Closely Coupled configuration (VT4886 stacked on top of VT4883 or suspended below VT4883)
Enable optional Input PEQ1 for use in Physically Separate configurations
(VT4886 + UB-1 + SS5-BK extension rod + VT4883 or flown VT4886 + ground stacked VT4883)

Warning: non-mixed subwoofer configuration - exercise caution when recalling presets and circuiting VT4886