

JBL PD6212/43 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6212/43 FR IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+4dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	131Hz
Filter #1 Gain	-2.0dB
Filter #1 Q	Q2.0
Filter #2 Type	Parametric EQ
Filter #2 Frequency	242Hz
Filter #2 Gain	-1.6dB
Filter #2 Q	Q4.2
Filter #3 Type	Parametric EQ
Filter #3 Frequency	565Hz
Filter #3 Gain	-5.5dB
Filter #3 Q	Q2.4
Filter #4 Type	Parametric EQ
Filter #4 Frequency	1kHz
Filter #4 Gain	+2.3dB
Filter #4 Q	Q3.5
Filter #5 Type	Parametric EQ
Filter #5 Frequency	1.475kHz
Filter #5 Gain	-2.3dB
Filter #5 Q	Q3.4
Filter #6 Type	Parametric EQ
Filter #6 Frequency	2.47kHz
Filter #6 Gain	-6.4dB
Filter #6 Q	Q1.8
Filter #7 Type	Parametric EQ
Filter #7 Frequency	4.285kHz
Filter #7 Gain	+1.7dB
Filter #7 Q	Q5.0
Filter #8 Type	Parametric EQ
Filter #8 Frequency	11.57kHz

Filter #8 Gain	-4.6dB
Filter #8 Q	Q4.0