

JBL PD6200/43 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/43 MHF IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	203Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+1dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	2556Hz
Filter #1 Gain	-6.5dB
Filter #1 Q	Q1.8
Filter #2 Type	Parametric EQ
Filter #2 Frequency	1.26kHz
Filter #2 Gain	-2.7dB
Filter #2 Q	Q3.0
Filter #3 Type	Parametric EQ
Filter #3 Frequency	419Hz
Filter #3 Gain	-2.3dB
Filter #3 Q	Q1.98
Filter #4 Type	Parametric EQ
Filter #4 Frequency	1658Hz
Filter #4 Gain	+3.9dB
Filter #4 Q	Q7.0
Filter #5 Type	Parametric EQ
Filter #5 Frequency	8.1kHz
Filter #5 Gain	-1.7dB
Filter #5 Q	Q1.6
Filter #6 Type	Parametric EQ
Filter #6 Frequency	240Hz
Filter #6 Gain	+1.1dB
Filter #6 Q	Q3.1
Filter #7 Type	Parametric EQ
Filter #7 Frequency	631Hz
Filter #7 Gain	-2.4dB
Filter #7 Q	Q1.45
Filter #8 Type	Parametric EQ
Filter #8 Frequency	12.75kHz

Filter #8 Gain	+3.0dB
Filter #8 Q	Q3.7