

JBL PD6212/66 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6212/66 FR IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	84Hz
Filter #1 Gain	-1.3dB
Filter #1 Q	Q3.0
Filter #2 Type	Parametric EQ
Filter #2 Frequency	165Hz
Filter #2 Gain	+7.0dB
Filter #2 Q	Q1.8
Filter #3 Type	Parametric EQ
Filter #3 Frequency	481Hz
Filter #3 Gain	-1.7dB
Filter #3 Q	Q1.8
Filter #4 Type	Parametric EQ
Filter #4 Frequency	837Hz
Filter #4 Gain	+8.5dB
Filter #4 Q	Q8.0
Filter #5 Type	Parametric EQ
Filter #5 Frequency	1087Hz
Filter #5 Gain	+3.6dB
Filter #5 Q	Q3.7
Filter #6 Type	Parametric EQ
Filter #6 Frequency	2.55kHz
Filter #6 Gain	-2.0dB
Filter #6 Q	Q0.8
Filter #7 Type	Parametric EQ
Filter #7 Frequency	7.1kHz
Filter #7 Gain	+2.0dB
Filter #7 Q	Q5.0
Filter #8 Type	Parametric EQ
Filter #8 Frequency	9.7kHz

Filter #8 Gain	+4.3dB
Filter #8 Q	Q2.1