

JBL PD6212/95 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6212/95 FR FIR
High Pass Type (IIR)	Butterworth 24dB/oct
High Pass Frequency	76.7Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	98Hz
Filter #1 Gain	-3.5dB
Filter #1 Q	Q3.8
Filter #2 Type	Parametric EQ
Filter #2 Frequency	132Hz
Filter #2 Gain	+9.5dB
Filter #2 Q	Q1.57
Filter #3 Type	Parametric EQ
Filter #3 Frequency	192.5Hz
Filter #3 Gain	+0.9dB
Filter #3 Q	Q4.46
Filter #4 Type	Parametric EQ
Filter #4 Frequency	315Hz
Filter #4 Gain	-1.9dB
Filter #4 Q	Q3.44
Filter #5 Type	Parametric EQ
Filter #5 Frequency	471Hz
Filter #5 Gain	+1.6dB
Filter #5 Q	Q4.0
Filter #6 Type	Parametric EQ
Filter #6 Frequency	730Hz
Filter #6 Gain	+1.8dB
Filter #6 Q	Q2.89
Filter #7 Type	Parametric EQ
Filter #7 Frequency	790Hz
Filter #7 Gain	-2.0dB
Filter #7 Q	Q9.0