

JBL PD6200/66 Passive FIR Rotated Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6200/66-H MHF FIR
High Pass Type (IIR)	Butterworth 24dB/oct
High Pass Frequency	206Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+1dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	230Hz
Filter #1 Gain	+1.5dB
Filter #1 Q	Q3.3
Filter #2 Type	Parametric EQ
Filter #2 Frequency	580Hz
Filter #2 Gain	-6.4dB
Filter #2 Q	Q1.1